

CARL MARTIN

Manual



The function of a wah pedal is to manually (by way of a rocker control) modulate your guitars' signal. Plug your guitar into the wah (input right) and then to other pedals, or your amp (output left). The 2 Wah is powered either by a 9v battery or a regulated 9v power supply (we always recommend the Carl Martin Big John Power Supply). By stepping on the front of the rocker, you engage the on-off switch, and by stepping on the back of the rocker you engage the Mode switch. Select position 1, 2, or 3 in both High and Low Modes, engage the effect and fine-tune the attack of this effect by adjusting the Attack knob (also on the front of the 2 Wah). The green (Low) and red (High) LED's indicate which Mode you are in, with Low being typically for lead work, and High being used more often for rhythm work.



The standard effect on-off by stepping on the front of the rocker to engage the true bypass on-off switch.



Select position 1, 2, or 3 in both High and Low Modes, engage the effect and fine-tune the attack of this effect by adjusting the Attack knob (also on the front of the 2 Wah). The green (Low) and red (High) LED's indicate which Mode you are in, with Low being typically for lead work, and High being used more often for rhythm work.



By stepping on the back of the rocker you engage the Mode switch, between low and high mode.

Specifications

Input..... 500K Ohm
Output..... 10K Ohm
S/N Ratio..... 58dB
Attack Potentiometer..... Q rate
3 Pos Mode Switch..... High & Low Eq.
Dimensions 265 (W) x 95 (D) x 80 (H) mm
10,42" (W) x 3.74" (D) x 3,15" (H)
Weight..... 2,2kg / 4,45lbs

Power Requirements

Battery: The 2Wah requires a 9V battery. To replace the battery, carefully remove the battery lid in the bottom, install the new battery and then re-install the battery lid.
Power consumption: max. 10 mA Min.
Power supply: 9 V DC (regulated), 20 mA minimum, 2.1 mm female plug, center negative (-)
ATTENTION: Please Use DC Power Supply Only!
Failure to do so may damage the unit and void the warranty.

Warranty: Carl Martin Research warrants the manufacturing, material and proper operation for a period of one year from date of purchase. Carl Martin will replace defective parts, make necessary repairs or replace the unit at the discretion of our technicians. The warranty applies only to the original purchaser of this product, and excludes any damage or faulty operation resulting from misuse, neglect or unauthorized service.

Made in China

East Sound Research Raadmansvej 24 8500 Grenaa Denmark Phone: +4586325100
E-Mail: info@carlmartin.com