

## STANDARD 102HF (8 and 4 ohm versions)



Speaker Size	2 x 10"
Tweeter	1" compression driver
CAB Power Handling (AES Standard)	400W RMS
Crossover Frequency	3.5 kHz
Frequency Response	40Hz to 20KHz
Sensitivity dB SPL	101
Impedance	8 or 4 ohms
Reflex	Front
Dimensions	23.4" / 59.5 cm (w); 18.7" / 47.5cm (h); 18.9" / 48 cm(d)
Weight	38.58 lbs / 17.5 kg

The **Standard 102HF** is recommended for bass players who need a **smaller pro-sounding rig**, or for those who like to combine cabinets, for example by adding a 102HF to a Standard 151 HR. Rated at **400 watts** (RMS), this small cab packs an **impressive punch** for its size!

### SUGGESTED SELLING POINTS

#### > **Power handling-to-weight ratio / portability**

The **Standard 102HF** contains ultra-light neodymium speakers. This cab weighs only **38.58 lbs / 17.5 kg**, with **400 watts** (RMS) of power handling.

#### > **Practical cabinet with a big sound**

The **Standard 102HF** is the perfect compromise between the Traveler 102P and a 4x10—it has a **bigger sound** than the Traveler 2x10, but is **easier to transport** than a 4x10. Great for **rehearsal halls** and **small to medium venues**.

#### > **8 and 4 ohm versions**

This cabinet is available in both **8 ohm** (Standard 102 HF-8) and **4 ohm** (Standard 102 HF-4) versions. The 4 ohm is recommended if you know you won't ever need or want to add a second cabinet, since it draws the **maximum power** from the head. If you use the 8 ohm version, you have the option to **add a second 8 ohm cabinet** anytime you need a bigger, louder rig.

#### > **Tweeter Level Control**

There's a **tweeter level attenuator** conveniently located on the side of all Markbass cabinets. This allows you to control the tweeter output as you stand in front of the cabinet, listening to the results.